


THE API

A²D

**DUAL 312 MIC PREAMPS
WITH DIGITAL OUTPUT**



API, 8301 Patuxent Range Road, Jessup, MD 20794 Tel: 301-776-7879
www.apiaudio.com

A BASIC OVERVIEW OF THE API A²D MIC PREAMP

Thank you for choosing the API A²D Microphone Preamp.

The A²D represents a landmark achievement for API; it is the first product ever produced by the company with an integrated digital output. Recognizing the desire for a high quality solution to raise microphone signals to a workable line level, we engineered one of our most popular mic preamp designs into an enclosure with the best analog to digital conversion that we could find. The result is a complete package - a pair of superb mic preamps feeding an A/D section with a set of standard digital interface outputs, multiple sample-rate choices, and internal or external clock options. Precise control of both the analog gain as well as the level feeding the digital section means that the mic signal can be maintained super-clean if desired, or driven harder on the analog side for that whallop and impact that can only be achieved by driving the transformer into saturation for that historic API sound!

The A²D analog section consists of the circuitry contained in two API 312 mic preamps, or one half of the popular 3124 quad mic preamp rack product. A level control pot with an expanded 20-segment metering system shows precise mic gain levels. Control switches include polarity, 48v phantom power, input pad, 2:1 transformer routing, and Mic/Line select. Each analog input contains a balanced low-level XLR connector and a high-level line input on a 1/4 inch jack.

The Digital section of the A²D includes two level pots to adjust the feed to the A/D converters, each with a corresponding 20-segment calibrated meter. A multi-position switch selects the desired sample frequency. The External Sync LED will light when an external clock signal is used.


Rear panel Analog connectors include an XLR input and output for each channel, as well as a balanced 1/4" TRS insert to the A/D converter. This allows the A²D to have external analog processing devices inserted in the audio chain (EQ, compression, etc.)

Digital interface connectors provided are SPDIF single ended RCA connector and AES digital out on XLR. A coaxial BNC accepts external "Super Clock" which will illuminate the front panel EXT SYNC LED when locked.

In addition, there are a pair of 9-pin D-sub connectors which allow the linking of multiple A²D units, all operating off the **first** sample-rate clock in the chain.

Analog Mic/Line Input Section - (Analog A and B)

There are two identical sections **Analog A** and **Analog B**. Each have the signature 3124 Microphone preamp design.



GAIN:

The GAIN pot sets the input signal gain and has a minimum gain of +34dB and a max of +65dB. Microphone input impedance is 1500ohms.

POL:

Changes the polarity of the microphone input only (not the line input).

48V:

Applies Positive 48v to the microphone input to power condenser-type mics.

PAD:

Input attenuation Pad of 20dB

2:1:


Attenuation of -10dB by tap selection on the Microphone preamp output transformer. This reduces the amount of gain created by the output transformer itself, and allows the 2520 amplifier to be operated at higher gain, if desired.

MIC: When selected (Lit), the Microphone input on the rear panel is the active input.

LINE:

Direct Input with High Z - [impedance]

Digital Section




LEVEL:

There are two digital input level controls. The range of the pot is infinity to unity. They are completely independent of each other, and are fed from their respective Analog A or B gain stage. If you are feeding the Digital section with a calibrated level, the inputs at unity will deliver the same calibrated level to the A/D converter.

METERS:

Range is infinity to unity. The meters have a fast attack peak reading characteristic with a 0dBFS full scale range. The LED's are yellow at -12 and -9 and red at -6, -3 and 0 to allow plenty of headroom warning as the input limit of the A/D section is approached.

Digital Section



Sample Rate select knob:

192, 176.4, 96, 88.2, 48, 44.1 (KHz) LED will indicate the current sample rate selected.

External Sync / Lock:


This LED will be lit when the A²D is receiving an external clock signal and is locked to that external signal, OR when the A²D is linked as a slaved unit in a chain.

NOTE:

When the A²D is slaved, the Sample frequency LED's do NOT light. This is because the master unit is providing both the sample frequency and the indication.

When Super Clock (Sync) input is used, the Ext Sync LED will be lit, but the actual A/D sample frequency is selected via the Sample Rate switch.

Rear Panel Audio Section



INPUT:

This is a microphone input - XLR type. The connector is wired pin 2 'hot' or positive.


OUTPUT:

This is a line-level output of the mic preamp - XLR type. The setting of the front-panel 'GAIN' pot will vary this output level as it simultaneously feeds the A/D side of the A²D. This connector is also wired pin 2 'hot' or positive.

A to D INPUT:

Analog Line Input 1/4" connector. This connector is an "insert" direct to the Analog to Digital converters. The XLR Output signal is normalized to the inputs of the jack. This is a balanced input and can accept input signals of up to +30dB.

Rear Panel Digital Section



SPDIF OUTPUT:

Sony Phillips Digital Interface Format single ended RCA connection.

AES/EBU OUTPUT:

Single wire AES standard digital interface.

SYNC IN:

BNC connection to apply an external Super Clock to the digital converter. If this connector is used and the unit is locked to an external clock, the front panel 'EXT SYNC' LED will be lit.

NOTE:

The actual sample rate that operates the A²D is derived from the Super Clock when the Sync In is used. So, a 22.579MHz clock will give multiples of 44.1k rates, and a 24.576MHz clock will give multiples of 48k.

MASTER OUT/SLAVE IN CONNECTORS:


D-Sub connection to couple multiple A²D units. The FIRST unit in the chain will become the master unit and all linked units will receive digital clock from the master. **A STRAIGHT THROUGH 9-pin cable must be used to link A²D units.**

NOTE: When linking two or more separate A²D units, both units must be set for the same sampling frequency via the front panel rotary Frequency Select switches BEFORE connecting the link, in order for the link to function properly.

DIGITAL OUT PANEL:

This panel is provided to allow for future additional digital output options.

Rear Panel Power



VOLTAGE SELECT:

Slide switch to select input AC voltage.

FUSE:

AC line fuse.

Only replace with the proper fuse for the appropriate AC input.

AC POWER PLUG:

IEC-type grounded AC input plug.

Specifications

Analog:

Input Impedance:	1500 Ohms Mic 470K Ohms Un-Balanced, HI-Z in
Output Impedance:	Less than 75 Ohms
Nominal Channel Output Levels:	XLR +4dBu
Output Clipping Level:	XLR: better than +28dBm
Frequency Response:	+0, -5, 10Hz to 20kHz (-.5 at 10Hz)
Noise EIN:	-129 Mic, -125 Un-Bal. Actual
Measured Noise:	Better than -91dBm / below Nominal +4
Distortion:	All Outputs at +4 out, .03%, at +22, .09% Max
Gain Range:	150 Ohms Input 10dB Min., 65 dB Max (inc. PAD). Un-Bal. Input 14dB Min., 50 dB Max
VU Meter:	Calibrated for XLR Outputs, OVU=+4dBu
Controls:	GAIN, POL (polarity), 48Volts, PAD (20dB), 2:1 trans. attenuation, MIC (mic/unbal)

Current draw:	130mA AC
Weight:	10lbs
Size:	19" X 8" x 1RU

Specifications

Digital: Input test signal is a 1 kHz sine wave; measurement bandwidth is 10 Hz to 20 kHz.

48K Performance

Dynamic Range	A-weighted	120dB
	unweighted	117dB
THD+N	-1dB	-110dB
	-20dB	-97dB
	-60dB	-57dB
Total Group Delay	250us	

96K Performance

Dynamic Range	A-weighted	120dB
	unweighted	117dB
THD+N	-1dB	-110dB
	-20dB	-97dB
	-60dB	-57dB
Total Group Delay	94us	

192K Performance

Dynamic Range	A-weighted	120dB
	unweighted	117dB
THD+N	-1dB	-110dB
	-20dB	-97dB
	-60dB	-57dB
Total Group Delay	26us	

Input Impedance	30K (ohms)
Interchannel isolation - all modes	110dB
Analog input CMRR	100dB
Phase Deviation @20hz	10Deg
Gain Drift - DC accuracy	+/-100ppm/°C

Housekeeping:

Here is a great place to write down the serial number of your A²D and your purchase date, just in case you need that information someday in the future. It's nothing but frustrating to have to unrack your equipment and search for the serial number years after a purchase. (and serial numbers are so easy to forget)

API A²D serial number _____

Purchase date: ____ / ____ / ____



API is division of Audio Toys, Inc., 8301 Patuxent Range Road, Jessup, MD 20794
Tel: 301-776-7879
www.apiaudio.com

In a constant effort to improve the subtle details of our products, some amount of change is inevitable.
API reserves the right to modify or change any of the features, specifications or performance of its products without notice or obligation.