



### Registering the Keychain Remote with the X-10 PRO Security Console

- Fit two AAA Alkaline batteries in the battery compartment in the back of the Keychain Remote.
- Press and hold the ARM button for about a second. The LED indicator flashes twice when you release it. This confirms the Keychain Remote has generated a new security code.
- Set the slider switch on the Security Console (i.e. PRO2000) to INSTALL.
- Press ARM. The console chimes once to confirm that the Keychain Remote has been registered.
- Return the console slider switch to the RUN1 or RUN2 position.

### Testing the Keychain Remote

- Set the slider switch on the Security Console to RUN1 or RUN2.
- Press ARM on the Keychain Remote. The console chimes once to confirm and the ARM indicator lights.
- **Note:** *The Keychain Remote always arms the system instantly - there is no exit or entry delay.*
- Press LIGHTS ON and LIGHTS OFF to turn on and off a light connected to a lamp module with codewheels set to A13 (or other code downloaded by the installing security firm).
- Press ARM and DISARM together to trip the panic alarm. Press DISARM to stop the alarm.

*Note: As with all RF transmitter devices; electrical fields, metal doors and appliances can cause interference that can decrease the strength of the transmitted signal. Re-orienting the transmitter or receiver console may increase your ability to send and receive the necessary signals.*