



Description:

The 6 Zone Annunciator is a flush mounted plate with 6 LEDs that represent each station location on the system. A tone will sound any time a call is placed on the system. The tone volume can be adjusted from low to high and momentarily muted with a three position toggle switch. The Annunciator is available in white powder coated Galvanized Steel or Stainless Steel.

Operation:

When a device is activated, the associated LED will illuminate steady or flash depending on the type of Switch Station. Once the call has been cancelled, the light and tone will shut off. If a registered switch is lost from the system, that associated LED will light up purple. It will also sound a steady tone indicating an error. All LEDs will illuminate purple and a steady tone will sound if there is a critical system failure.

Technical Specifications:

- RJ45 connectors:
 - 1 IN and 1 OUT
 - 6 Switch Station connections
- 24 AWG, 8 conductor
- Product material: 16 AWG Galvanized or Stainless Steel
- Back box material: 18 AWG Galvanized Steel
- Dimensions:
 - Face plate:** 5.75" H x 10.25" W x 2.63" D
 - Back box:** 4" H x 8.5" W x 2.63" D
- Weight: 2.67 lbs