



Secondary tablet  
for the IQ Panel



IQ2



Power supply



Table Stand



Optional wall mount patch

## NEED HELP?

(855) 4-QOLSYS

TECHSUPPORT@QOLSYS.COM

### INFORMATION

Document#: IQ2-QG-05-15

Revision#: 5/11/15

Issue Date: MAY 2015

Qolsys Part #: QW9100-840-00

Software : IQ2-1.4

Additional documentation located on Qolsys.com

The IQ2 is a 7" secondary tablet that can be installed to create additional access to the IQ Panel. You can pair up to three (3) of these tablets with the IQ Panel.

### STEP 1: CONNECTING POWER



Connect the power supply into the plug marked "DC-5V" on the side of the display.

### STEP 2: POWERING ON THE IQ2



Press and hold the power button until the screen illuminates (approx 3-5 sec)

### STEP 3: CONNECTING THE IQ2 TO WI-FI



The IQ2 pairs with the IQ Panel over a Wi-Fi Network (802.11 B, G, N) and must be connected to the same network as the IQ Panel before you can add it to the system.

To connect to Wi-Fi:



MORE

Touch "More"

WiFi Settings

Touch "WiFi Settings"

WIRELESS & NETWORKS

Wi-Fi

Make sure Wi-Fi is turned on (swipe to the right)



Select Wi-Fi network from available list.



Enter Wi-Fi network password if required.

**IMPORTANT:** Please check that the IQ2 can successfully connect to the network in the chosen installation location

## STEP 4: PAIRING THE IQ2 WITH THE IQ PANEL



Touch  
"Settings"



Enter installer code  
(default is 1111)



Touch  
"Installation"



Touch  
"Security  
Account"

IQ2 Panel  
Support IQ2 control panel Enabled



Scroll to the bottom of the page and make sure  
the box next to "IQ2 Panel" is checked.



Touch "Back"  
twice to get to the  
Settings page



Touch "IQ2  
Devices"



Touch "Add  
New"



Touch "Device Name"  
to open the on-  
screen keyboard



Create a unique name for the IQ2  
(15 characters max, numbers and  
letters only, no special characters)



Enter the IP Address of the IQ2\*  
into the appropriate field on the  
IQ Panel then touch "Save"




The IQ2 will take a  
moment to synchronize  
with the IQ Panel over  
the network. Once  
complete it will display the home screen.

To add additional IQ2 tablets repeat steps  
above with up to three (3) total devices.


\*To find the IP Address of the IQ2:



Touch "More"



Scroll down to "About"



Locate "IP Address"

## TROUBLESHOOTING

### Message:

- Network Connection Failed
- Loading data from primary panel
- Please register your IQ2 panel with the primary panel

### Try the following solutions in this order:

- 1- Check that the Wi-Fi network is active and that both the IQ Panel and IQ2 are connected to the same network.
- 2- From the IQ Panel, "Ping" your IQ2. (Touch "Settings" enter installer code, touch "IQ2 Devices" then touch "Ping") Touch any tab on the IQ2 to refresh the page.
- 3- Reset the IQ2 (Touch "More" then "Reset") Repeat step 2.
- 4- Delete the IQ2 from the IQ Panel (Touch "Settings" then enter installer code, touch "IQ2 Devices")