

Azur 550T Tuner



- Pure FM/AM in the true analogue domain
- Refined board layout
- Brand new wrap-around casework design with substantially thicker brushed aluminium front panel
- Sophisticated Alarm and Sleep timer functions
- Control Bus inputs and outputs to turn on and off connected Cambridge Audio amplifiers
- Supplied with the Azur Navigator remote control
- Available in silver and black finishes

Detailed Specifications

Frequency Range	FM (87.5 – 108MHz) Europe FM (88 – 108MHz) US AM (531 – 1602kHz) Europe AM (530 – 1710kHz) US
Aerial Inputs	75 ohms unbalanced (FM) 50 ohms unbalanced (AM)
FM Sensitivity	-25dBm typical
Signal to Noise	50dB typical (FM) 47dB typical (AM)
FM Frequency Response (+/-3dB)	20Hz – 15kHz
Distortion	<0.3%, @ 1kHz, 50kHz deviation (FM) <0.9%, @ 1kHz (AM)
Stereo Separation @ 1kHz	>50dB (FM)
Maximum Power Consumption	7W
Standby Power Consumption	6.5W
Dimensions (HxWxD)	70 x 430 x 305mm (2.75 x 16.9 x 12")
Weight (unboxed)	4.1kg (9lbs)
Weight (boxed)	5.6kg (12.3lbs)



Azur 550T Tuner