

CC4001

5 DISC CD CHANGER



The CC4001 makes a new statement about the desirability of owning a carousel disc changer with its aluminum front panel design. Unlike most other changers, the circuitry features SA-CD grade Cirrus Logic 4392 digital-to-analog converters for the finest sound quality you've ever experienced from a multi-disc unit. You can select the disc you want from the front panel in addition to choosing it remotely. The CC4001 handles CDs, their recordable CD-R and CD-RW cousins, and MP3-encoded discs, too. Custom-installation conveniences include a bi-directional RS232C connector, a detachable AC cord, and an infrared flasher input. Hidden inside is a set of five discrete IR code sets for multiple-user convenience. The sound quality? Well, we've already mentioned the critical D/A converters. So we'll just ask you this question – would we use those parts if the rest of the circuitry didn't demand that level of performance? Of course not. But, then, the CC4001 is a Marantz after all.

- Bi-directional 5 disc carousel mechanism
- Plays CD, CD-R/RW, MP3 playback
- SACD Grade Cirrus Logic CS4392 DAC
- Direct disc access button
- Headphone jack with volume
- 5 Discrete IR Code sets for multiple use
- Various play modes (Random, Program, Repeat, and AMS)
- Bi-Directional RS232C control
- Coaxial and Optical digital output
- IR Flasher Input
- Detachable AC Cord
- Device remote
- Aluminum front panel
- Three year limited warranty



MP3



marantz®

LIFE AMPLIFIED™

*All specifications, dimensions and weights are subject to change without notice.
D&M Holdings, Marantz, Marantz America, Inc. or any of its subsidiaries will not assume any liability for errors in this spec sheet which may result in consequential errors being made by retail dealers, designers, custom installers, cabinet makers or end users, etc based upon information contained within this document.

©2006 Marantz America, Inc. • www.marantz.com

5 DISC CD CHANGER

FEATURES

Disc Capacity	5
Playback Formats	CD, CD-R/RW, MP3
Power Transformer	EI
Audio DAC	192kHz/24-Bit
Random/Repeat Play	¥
Recording Edit Mode	-
AMS (Auto Music Scan) Mode	¥
Peak Search	-
Pitch Control	-
Disc Changeable In Play	¥ (4 Discs)
Headphone Level Control	¥
CD Text	-
Display On/Off	¥ (Dimmer)
Multiple IR Ocde Set	¥ (5 Sets)
Detachable AC Cord	¥

IN/OUTPUTS

AUDIO	
Analog L&R Out	1
Digital Optical Out	1
Digital Coaxial Out	1
Headphone Out	¥
OTHER	
External Control (RS-232C)	¥ (2-way)
IR Flasher In	¥
D-Bus Remote (RC-5) In/out	1/1

SPECIFICATIONS

AUDIO SECTION	
Format	16-Bit Linear PCM
Sampling Frequency	44.1kHz
Dynamic Range	100 dB
Frequency Response	2Hz - 20kHz
THD	0.0020%
S/N ratio	115 dB
GENERAL	
Color	Black
Faceplate	Aluminum
Remote	Device remote RC4001CC
Power Requirement	AC 120V 60Hz
Power Consumption	18W
Dimensions W x H x D (Inches)	17 5/16" x 4 1/2" x 15 15/16"
Weight (lbs.)	15.2

Compatible

Life Amplified™

*All specifications, dimensions and weights are subject to change without notice.
 D&M Holdings, Marantz, Marantz America, Inc. or any of its subsidiaries will not assume any liability for errors in this spec sheet which may result in consequential errors being made by retail dealers, designers, custom installers, cabinet makers or end users, etc based upon information contained within this document.

©2006 Marantz America, Inc. ¥ www.marantz.com